

Murray City Power

Utility Electrical Service Entrance

Line

NET
(Bidirectional)
Power Meter

Main
Disconnect

Load

PRODUCTION
Power Meter

Photovoltaic
AC
Disconnect
Switch

Photovoltaic
Inverter

Photovoltaic
Panels

Solar
Generation
On-Site

Solar
Generation
On-Site

Solar AC
Disconnect

Label

Net meter base, production meter base, and solar AC disconnect engraved labels must be mechanically fastened with rivets, screws, or bolts.

Disconnect switch must be manually operated with visible contacts. (Circuit breakers or inverter integrated disconnects do not satisfy this requirement.)

6' Max.
4' Min.

6' Max.

Must Be Grouped

Final Grade